



PHONE: 785.827.9278

EMAIL: sales@future-retro.com

ONLINE: www.future-retro.com

MOBIUS UPGRADE INSTALLATION

Please follow all directions carefully and in the order that follows.

1. Make sure the power is off and the power supply has been disconnected from the unit.
2. Remove the four black hex screws on the front panel, using a 7/64" hex driver. You should also remove the Glide time control knob, and the hex nut/washer which secures the Glide time control to the front panel.
3. The front panel may now be removed from the unit.

NOTE: While handling the processor, it is important to avoid any static discharge. Open the processor packaging near where you are working with the unit. Avoid walking around while handling the processor!!!

4. Locate the processor just to the left of the four digit display (see figure below left).
5. Notice the semicircle indicator on the processor and the direction it faces. It is very important that the new processors indicator faces the same direction.
6. Place a small flat-blade screwdriver between the bottom of the processor and the top of its socket (see figure below right). Gently twist the screwdriver to remove the processor from its socket.
7. Lay the new OS upgrade processor on the socket and make sure its pins are lined up with the socket. Again, make sure the processors indicator is located in the position as shown below.
8. Press the processor into its socket until it is fully seated.
9. Place the front panel back on the unit (may need to install the Glide time control first).
10. Reinstall the mounting hardware for the Glide time control and the four black hex screws.
11. Connect the AC power adapter to the unit.

You will now need to perform a soft reset to the machine to initialize the new OS (steps 12 and 13).

12. With the units power off, hold Step key 1 in the sequencer section and turn the units power on.
13. Continue to hold Step key 1 until the mobius pattern leaves the display, and operation will return to normal.

NOTE: Due to the fact that the Mobius is always saving your changes while you work it is important that you stop playback and are not performing editing procedures when the units power is turned off. Should the units power be turned off while it is saving parameters, there is a chance the parameters will not be saved correctly causing the unit to appear to be stuck in a loop the next time it is powered on. Should this ever happen you can use the soft reset procedure above to return the units operation to normal. This will not harm your internal patterns and songs.

Note location of the processors' indicator.

